



we connect your world



MODEL	SWM-E4
DESCRIPTION	Quad SWM Expander
ORDER #	217530
FEATURES	
Enables easy expansion number of connected SWM modules	
SPECIFICATIONS	
Frequency Range	250 - 2150 MHz
Number of Inputs	6
Number of Outputs	24
Number of DC Inputs	2
Number of DC Outputs	4
Insertion Loss	10 max dB
Flatness @ 24 MHz	± 0.5 dB
Input and Output Return Loss	> 8, Typ 10 dB
Isolation between Inputs / Outputs	> 40 dB
Operating Temperature Range	-34 to +60 (-31 to +140) °C(°F)
APPLICATION	
SWM Expanders are required for to increase number of connected SWM modules	